## Los Angeles Fire Department Community Emergency Response Team Communication Plan

## Version 3.5 - Effective September 22, 2014 THIS INFORMATION IS PROPRIETARY AND CONFIDENTIAL NOT FOR DISTRIBUTION WITHOUT STAFF APPROVAL

CERT Repeater Channels	CERT Channel 8 (2m - Primary)	CERT Channel 16 (70 cm - LA Basin and South)	CERT Channel 24 (70cm - Valley)		
Name	Coldwater Repeater (LAFD ACS Repeater)	Hughes Repeater W6HA	Southern California Mutual Aid Repeater		
Frequency	144.505	445.620	447.820		
Shift	PLUS	MINUS	MINUS		
PL	162.2	127.3	67		

CERT Battalion Level Tactical Channels										
CERT Simplex Channel #	CERT 1	CERT 2	CERT 3	CERT 4	CERT 5	CERT 6	CERT 7	CERT 9	CERT 10	
Use for: Primary Frequency PL (Tone)*	Battalion 1 144.310 110.9*	Battalion 2 145.585 110.9*	Open 144.370 110.9*	Battalion 4 144.405 110.9*	Battalion 5 144.330 110.9*	Battalion 6 144.320 110.9*	Open 144.465 110.9*	Battalion 9 144.350 110.9*	Battalion 10 144.475 110.9*	
Secondary Frequency  CERT Simplex Channel #	CERT 15	CERT 13  CERT 12	CERT 13	CERT 14	CERT 6	CERT 5 CERT 17	CERT 18	CERT 3	CERT 18	
Use for: Frequency PL (Tone)*	Battalion 11 145.525 110.9*	Battalion 12 144.435 110.9*	Battalion 13 145.540 110.9*	Battalion 14 147.48 110.9*	Battalion 15 144.340 110.9*	Battalion 17 144.360 110.9*	Battalion 18 147.510 110.9*	Alt 1 146.445 110.9*	Alt 2 147.525 110.9*	
Secondary Frequency	CERT 12	CERT 11	CERT 2	CERT 4	CERT 1	CERT 7	CERT 10			

CERT Division Level Channels				Additional Frequencies			
CERT Division Channel #	CERT Division Channel # CERT 21 CERT 22 CERT 23		CERT 23	National Calling Frequency	TBD	TBD	
Use for:	North Division	Open	South Division	National Calling Frequency			
Frequency	146.535	146.460	146.595	146.520			
PL (Tone)	110.9*	110.9	110.9*	Use for contact than move to another frequency			

## **CERT Comm Plan Notes**

- 1 CERT Channel 8 is the Primary CERT Repeater. It is also the ACS Secondary Repeater. Use for initial contacts only if necessary and move immediately to a simplex frequency. We have permission to use this repeater, but use it only if it is not busy and we do not interfere ACS communications.
- 2 CERT Channel 16 is a 70cm repeater for the LA Basin and belongs to the Hughes Amateur Radio Club. Use for initial contacts only and move .immediantly to a simplex channel. We have permission to use this repeater, but use it only if it is not busy and we do not interfere with their communications.
- 3 CERT Channel 24 is a 70cm repeater for the Valley and belongs to the Municipal Amateur Radio System and is used by the Southern California Mutual Aid Network.

  Use for initial contacts only and move to a simplex channel. We have permission to use this repeater only if it is not busy and we do not interfere with SCMA communications.
- 4 All CERT Channels with the exception of the repeater Channels 8 and 16 and 24 are Simplex frequencies. Use the lowest workable power settings.
  - \* Simplex PL tones shall be programmed as "TONE" (encode) but not "CTCSS" (decode).
- 5 Use the Battalion Level Comm Channels for Battalion wide and Battalion to Division comms only. NOT FOR LOCAL TACTICAL USE
- 6 CERT Division Level Channels 21, 22 and 23 are reserved for Battalion Station to the Division Stations comms only. NOT LOCAL FOR TACTICAL USE
- 7 USE FRS CHANNELS FOR TACTICAL COMMUNICATIONS
  - In the South Division, Use FRS Channel 11, no code, for initial tactical contact and switch to another channel.
  - In the North Division use FRS Channel 7 code 88.5 for initial tactical contact then switch to another channel. Do not use FRS 7 in the Topanga Canyon area.
- 8 Version 3.5 adds frequencies to CERT 3, 7 and 22 for use as secondary frequencies.